



**SPECIFICATIONS**

<b>Supply Voltage</b>	24 VDC or 24 VAC, +/- 10%, 50 or 60 Hz	
<b>Supply Current</b>	105 mA maximum w/o 24 VDC auxiliary output	190 mA maximum w/ 24 VDC auxiliary output
<b>Input Ranges (Jumper Selectable)</b>	0-5 VDC, 0-10 VDC, 0-15 VDC, 0-20 mA	
<b>Input Ranges with Offset Jumper</b>	1-5 VDC, 2-10 VDC, 3-15 VDC, 4-20 mA	
<b>Input Impedances (Nominal)</b>	Voltage/10,000Ω nominal	Current/250Ω nominal
<b>Output (Floating Point)</b>	Two relay contact outputs (Increase/Decrease)	
<b>Relay Contact Ratings</b>	Form C, 2A maximum @ 24V	
<b>Output Accuracy</b>	2% Full Scale @ 32 to 120°F	
<b>Operating Temp/RH</b>	32 to 120°F (0 to 48.9°C)/10 to 95% non condensing	
<b>Product Dimensions</b>	(L) 3.45" (W) 4.00" (H) 1.15"	

**ORDERING**

Please select AFP as an Interface Device (A) and one Version (B). **NOTE:** Upon power-up, the decrease relay will drive 100% of the chosen timing range to ensure that the output is at its minimum position. Whenever the input on AFP Version 2 is within 2-5% of extreme up or down, the relay will activate for an additional time that is 100% of the selected timing range. To ensure that the control signal and actuator are in sync, each time the analog input signal reaches either the 2% to 5% level and below or 95% to 98% level and above, the increase or decrease contact will be driven to 100% of the selected full scale timing range.

**A** Interface Device      **B** Version

- AFP** (Analog to Floating Point (Tri-State) Output)
- (30, 60 or 90 Second Timing) (Standard)
- VERSION #2** (120, 150 or 180 Second Timing)
- VERSION #3** (14, 16.5 or 19 Second Timing)
- VERSION #4** (30, 60 or 90 Second Timing) (Relay Stay On @ Min/Max)
- VERSION #5** (90, 135 or 180 Second Timing) (Relay Stay On @ 5% Min/Max)
- VERSION #6** (18, 75 or 360 Second Timing)

**BUILD PART NUMBER**

After completing (A) & (B) from the above table, fill in the Part Number Table below. An example part number is offered.

**AFP**

A	B
---	---

EXAMPLE: AFP VERSION #2

